

**VIKING**<sup>®</sup>

*Made in the U.S.A.*

Telecommunication Peripheral Products  
**Technical Practice Addendum**

**TR-1**  
 Software Addendum  
 August 22, 1997

**TR-1 Software for Use Outside  
 of the United States**

Optional Software Available	Jumper 1	Jumper 2	Jumper 3	Jumper 4	Jumper 5	Jumper 6	Emergency Phone Number	Toll Free Number
TR1 (USA)	976, 1-976, 1-XXX-976	1-XXX-XXX, 10	0	1-900	555,1-555, 1-XXX-555, 411, 1-411	"9" PABX Mode	911	1-800, 1-888
TR1PRT (Portugal)	0XXXX	506	0670	00	090,099, 098	"0" PABX Mode	115	0500
TR1CHL (Chile)	0X	182	103	700	Not Used	"9" PABX Mode	13X	800
TR1URG (Uruguay)	0007, 0008	408	0-900	00-XXX	0-XXXX	"9" PABX Mode	999-109	0-800
TR1HKG (Hong Kong)	0X	00	Not Used	Not Used	Not Used	"9" PABX Mode	Not Used	Not Used
TR1IRE (Ireland)	0X	00	1190, 1191	1-850, 1-550	114	"9" PABX Mode	999	1-800
TR1NTH (Netherlands)	09, 00	068	06XX	Not Used	Not Used	"9" PABX Mode	0611, 112	Not Used
TR1BGM (Belgium)	00	0XX	1207, 1307	077	Not Used	"9" PABX Mode	100, 101	078
TR1PAN (Panama)	00	102	107, 108, 109, 115,	0X	106	"9" PABX Mode	103, 104	Not Used
TR1KWT (Kuwait)	00	011	101	1800	Not Used	"9" PABX Mode	119, 777	Not Used
TR1SGP (Singapore)	005	104	169, 161, 166, 900, 100, 163	1900	00X	"9" PABX Mode	999, 995	1-800
TR1FIN (Finland)	990	92022	118	9-XXXX, 109XX,101XX	9700, 0700	"0" PABX Mode	112	92015
TR1RUS (Russia)	810	8XXX	Not Used	Not Used	Not Used	"9" PABX Mode	01, 02, 03, 04	Not Used
TR1NZL (New Zealand)	00	0172	018	010, 0XXX	0900	"1" PABX Mode	111	0800
TR1THL (Thailand)	001	100	0XX	13, 183	101	"9" PABX Mode	17XXX,191,151, 152,161,162, 1144,1500,1501	088
TR1MEX (Mexico)	02	09	91XXX, 92	95, 96	98, 99	"9" PABX Mode	06, 08	91-800
TR1GUA (Guatemala)	00	171	0X	190, 195, 189, 191	124	"9" PABX Mode	122, 123	Not Used
TR1ARG (Argentina)	00	019	0XXX	110	Not Used	"9" PABX Mode	101	0-800
TR1CZH (Czech)	00	01XX	1XX	0XXX	Not Used	"9" PABX Mode	150,155, 158	Not Used
TR1ITA (Italy)	0X	170	1XXX	12, 175, 176, 1790, 1800	Not Used	"9" PABX Mode	113	1678
TR1TCI (Turks Caicos)	0	115	110	Not Used	Not Used	"9" PABX Mode	911, 999	Not Used
TR1SAU (Saudia Arabia)	0X, 9XX	00	Not Used	Not Used	Not Used	"9" PABX Mode	996, 997, 998, 999	Not Used
TR1HON (Honduras)	00	197	192, 194, 196	Not Used	Not Used	"9" PABX Mode	199	Not Used
TR1PHI (Philippines)	00	108	114	0XXX	Not Used	"0" PABX Mode	Not Used	0-800
TR1SPN (Spain)	07	025	003	91, 93, 96	Not Used	"9" PABX Mode	091	Not Used

**Product Support Hot-Line...(715) 386-8666**

**Fax Back Line...(715) 386-4345**

Due to the dynamic nature of the product design, the information contained in this document is subject to change without notice. Viking Electronics, its affiliates and/or subsidiaries assume no responsibility for errors and/or omissions contained in this information. Revisions of this document or new editions of it may be issued to incorporate such changes.