



# APPLICATION Note

**TELECOM SOLUTIONS FOR THE 21ST CENTURY**

## RC-2A

Using the RC-2A with a 4x4 Keypad

April 17, 2013

## Using the RC-2A with a 4x4 Keypad for Extreme Security Applications

**IMPORTANT:** This document is to be used in conjunction with the RC-2A Product Manual (DOD# 160).

### A. Legacy Programming (DIP Switch 5 OFF)

The RC-2A contains (3) rotary entry code switches. Using a small flat blade screwdriver, rotate the arrow on each switch to the desired access code setting.

1	2	3	A
4	5	6	B
7	8	9	C
* 0	#		D

Touch Tones	Switch Setting
0-9	0-9
#	C
B	E
C	F
(disabled)	D

### B. Alternative Programming (DIP Switch 5 ON)

The RC-2A contains (3) rotary entry code switches. Using a small flat blade screwdriver, rotate the arrow on each switch to the desired relay activation code setting.

1	2	3	A
4	5	6	B
7	8	9	C
* 0	#		D

Touch Tones	Switch Setting
0-9	0-9
*	B
#	C
A	D
B	E
(ignore)	F

Product Support Line...715.386.8666

Fax Back Line...715.386.4345

Due to the dynamic nature of the product design, the information contained in this document is subject to change without notice. Viking Electronics, and its affiliates and/or subsidiaries assume no responsibility for errors and omissions contained in this information. Revisions of this document or new editions of it may be issued to incorporate such changes.